



Innolytics, LLC
The Humane Hatch Control Company

P.O. Box 675935, Rancho Santa Fe, CA 92067
Tel: 858.759.8012 – FAX: 858.923.2060

Special Assembly Instructions for the **OvoControl[®] Large Tripod Feeder**

In addition to the assembly instructions, the effective operation of the *Large Tripod Feeder* requires several modifications for OvoControl use. Please follow the following additional instructions carefully.

- Depending on your order, either a 6-volt conventional battery or rechargeable battery is included. A conventional battery will last 3-6 months under typical operating conditions. A rechargeable battery with solar charger has an expected 3 year life.
- For optimum application of OvoControl bait, discard the three (3) white spacers located between the feeder bin and the guard. This will ensure the proper flow of OvoControl bait although limits the flow of WHOLE corn.
- Depending on the installation surface and number of installed leg sections, the scatter plate will broadcast bait in a 20ft to 40ft diameter circle.
- Depending on the site, not all leg sections are necessary. One short and one long extension will yield a 5ft feeder, suitable for most installations. Adding a leg extension will increase the scatter radius – removing an extension will reduce the broadcasting distance.
- The programming clock can be set for up to 6 feeding events, daily. The clock has been pre-programmed by the factory for baiting events #1 and #2. Most sites require just one daily feeding event shortly after sunrise. Zero out event #2 to avoid triggering the feeder more than once a day.
- Six (6) seconds on the clock delivers approximately 1 pound of OvoControl bait. Since corn kernels are much larger, the equivalent quantity of WHOLE corn requires more dispensing time than OvoControl. Follow the enclosed calibration instructions to ensure the feeder delivers the appropriate bait quantity. USE SAFETY GLASSES WHEN TESTING.
- Secure feeder to rooftop with a strap or other suitable method to prevent movement under windy conditions.
- Call your distributor or Innolytics for rechargeable batteries, solar panels or other feeder accessories.

Any questions or concerns? Please call Innolytics at 858.759.8012 or email info@ovocontrol.com.