



Innolytics, LLC
The Humane Hatch Control Company

*P.O. Box 675935, Rancho Santa Fe, CA 92067
Tel: 858.759.8012 – FAX: 858.923.2060*

OvoControl[®] Directional Feeder

Digital Timer Users Guide

Innolytics recommends the directional feeder to accurately dispense OvoControl for small flocks of pigeons – less than 40 birds. For larger flocks, we recommend the large tripod feeder which has 360° broadcast capability.

The digital timer on your new OvoControl Gravity Feeder can be set to feed up to 6 times per day. It has been factory set to feed just once a day at 6:30AM for 5 seconds. To change settings or add feeding times, follow the instructions below.

SET TIME OF DAY: Press the UP or DOWN button until the correct time of day appears. Press and release button to single-step through the minutes or hold down to advance quickly. The feeder will not run while buttons are being pressed and waits 10 seconds from the last button pressed before it is activated. The feeder is activated when the display alternates between the CURRENT TIME and %BATTERY.

SET FEED TIME: Press the SET button until the correct Timer Number appears in the upper right hand corner. Press the UP or DOWN button to set the Feed Time. Press the SET button again to set the RUN-TIME SECONDS which can range from zero to twenty seconds. Set the RUN-TIME SECONDS to zero to disable a specific time.

The gravity feeder will dispense the following quantities of OvoControl bait,

Seconds on Clock	Ounces Dispensed	Pigeons Treated
2	1.75	9
4	3.50	18
6	5.25	26
8	7.75	39

Set timer to dispense OvoControl at the rate of 4 ounces for 20 pigeons.

TEST TIMER: To test Timer, PRESS AND HOLD the SET button while the RUN-TIME SECONDS are displayed. Release the button when the message “TESTING GET AWAY” appears on the display. The display will countdown five seconds before activating the motor for the number of RUN-TIME SECONDS programmed. The test feature is useful for evaluating the amount of bait dispensed with each feeding event. See the Feeder Calibration Guide for complete instructions.

The Battery Level is displayed every seven seconds. It is recommended that the battery be replaced when the %BATTERY reading is 25% or below.

Innolytics Customer Service will gladly answer any questions you may have on OvoControl or the automatic feeders. Please call 858.759.8012 Monday – Friday from 8:00AM to 5:00OPM, Pacific Time. You can also visit www.ovocontrol.com for further information and details.